

XD-2L BR

MULTIPURPOSE DETECTOR

The XD-2L is a multipurpose wired detector, which can operate with any alarm control panel. The device can work as: magnetic contact, shock detector, shock detector and magnetic contact, and water flood detector.

The detector is available in white (**XD-2L**), brown (**XD-2L BR**) and dark grey (**XD-2L DG**).

- option to select detector type with DIP switches
 - modes of operation:
 - magnetic contact
 - detection of opening of a door, window, etc.
 - input for connecting an NC-type wired detector (e.g. other magnetic contact)
 - 1 alarm output
 - shock detector
 - detection of shocks and vibrations accompanying attempts to force a door or window, etc.
 - input for connecting an NC-type wired detector (e.g. other magnetic contact)
 - 1 alarm output
 - shock detector and magnetic contact
 - detection of shocks and vibrations accompanying attempts to force a door or window
 - detection of opening of a door, window, etc.
 - input for connecting an NC-type wired detector (e.g. other magnetic contact)
 - 1 or 2 alarm output(s)
 - water flood detector
 - detection of flooding in rooms with plumbing
 - input for connecting external flood probe **FPX-1** (white), **FPX-1 BR** (brown) or **FPX-1 DG** (dark grey) – the probe available separately
 - 1 alarm output
-
- option to select alarm output type (2EOL/NC or NC)
 - option to select EOL resistors for 2EOL configuration
 - alarm: 1.1 k Ω / 2.2 k Ω / 4.7 k Ω / 5.6 k Ω / 6.8 k Ω
 - tamper: 1.1 k Ω / 2.2 k Ω / 4.7 k Ω / 5.6 k Ω
 - LED indicator
 - remote enabling/disabling of the LED indicator
 - supply voltage control
 - tamper protection against enclosure opening
 - 2 magnets included (for surface and flush mounting)

