

ROP-111/EU

CONVENTIONAL MANUAL CALL POINT FOR OUTDOOR USE

The **ROP-111** call point is used to manually trigger an alarm when a fire is discovered. The call point is designed to work with the **CSP-104**, **CSP-108**, **CSP-204** and **CSP-208** fire alarm control panels.

- resettable plastic pane
- key to enable:
- testing
- resetting

LED to indicate activation of the call point
mounting box included

ROP-FLAP - optional protective cover to prevent unintentional activation

TECHNICAL DATA

| | |
|-------------------------------------|------------------|
| Operating temperature range | -25°C...+70°C |
| Weight | 180 g |
| Maximum humidity | 95% |
| Current draw when detecting | 0 mA |
| Current draw when emitting an alarm | 25 mA |
| IP rating | IP66 |
| Power supply voltage | 9...30 V DC |
| Dimensions without holders | 87 x 87 x 53 mm |
| Dimensions with holders | 117 x 87 x 53 mm |

