

ROP-401/EU

ADDRESSABLE MANUAL CALL POINT FOR OUTDOOR USE

The **ROP-400** call point for outdoor applications is used to manually trigger an alarm when a fire is discovered. It is designed to operate in the detection line of the **ACSP-402**; addressable fire alarm control panel.

- resettable plastic pane
- **ROP-KEY-U** key (sold in set) to enable:
 - testing
 - resetting

LED indicator/li>
double-sided short-circuit isolator
power supply from the detection line
mounting box included
optional protective cover to prevent unintentional activation - **ROP-FLAP**



TECHNICAL DATA

Operating temperature range	-25°C...+70°C
Weight	180 g
Maximum humidity	95%
Current draw when detecting	170 µA
Current draw when emitting an alarm	450 µA
IP rating	IP66
Power supply voltage	18...26 V DC
Dimensions without holders	87 x 87 x 53 mm
Dimensions with holders	117 x 87 x 53 mm