

SPP-400

ADDRESSABLE FIRE ALARM SOUNDER

The **SPP-400** indoor sounder is used for acoustic alarm signalling. It is designed to operate in the detection line of the **ACSP-402** addressable fire alarm control panel.

- acoustic signalling by means of piezoelectric transducer
- signalling controlled by the control panel:
 - different tones for different alarm conditions
 - 32 selectable tones
- double-sided short-circuit isolator
- power supply from the detection line
- available in red (**SPP-400**) and white (**SPP-400-W**)



TECHNICAL DATA

Operating temperature range	-10°C...+55°C
Weight	224 g
Maximum humidity	95%
Dimensions	108 x 108 x 87 mm
Current draw when detecting	250 µA
Current draw when emitting an alarm	4 mA
IP rating	IP21C
Power supply voltage	18...26 V DC
Operating environment	A

